

Omnia-6 Front Panel Software Upgrade (user interface)

The front panel software of Omnia-6 units currently running Display software version 1.0.4.0 and higher can be updated by downloading new code to it over the Ethernet connection. To use this feature, you must first have the proper front panel software update (.upd) file. This file can be obtained from Telos / Omnia Technical Support via email or from <http://www.omniaaudio.com/support/updates.htm>. Check back often to ensure that you have the benefit of the latest updates and features.

To install the update:

1. Find the .upd file obtained from Telos / Omnia Technical Support or download the latest front panel update from <http://www.omniaaudio.com/support/updates.htm>. We recommend downloading the file to a new folder on your PC's desktop for convenient access during the procedure.
2. Configure Omnia Remote Control (version 6.3.8 or higher) for connection to the Omnia over a network. Note that if you don't have a network, you can still use Ethernet if you use a crossover cable between the PC and Omnia. Such cables can be obtained from many computer products stores.
3. Connect to the Omnia over Ethernet.
4. Using the Options menu, navigate to the Upgrade Front Panel menu option. When you select it, an Open File dialog box will appear. Point the program to the folder on your PC where you downloaded the .upd file.
5. Select the 'omn6hd.upd' file and click the Open button. A message box will appear, detailing the process of downloading the file to the front panel. The update process can take several minutes, and may appear to be stuck at some points in the process. This is normal! Therefore do not interrupt the update! When the update is finished, a new message box will appear stating "Upgrade Successful".
6. It will now be necessary to reboot the unit in order to load and run the new software that was just downloaded. While the option exists for rebooting the unit via the front panel, we recommend a power off / on cycle for best results. This may be done immediately after downloading the update, or at a more convenient time if necessary.

Revised 2/13/2004